



## Overview

The FX80 Supervisory Controller is a web-based supervisory-class controller in the Facility Explorer® product family. The FX80 controller manages networks of field controllers using open communication protocols, such as BACnet®, LonWorks®, and the N2 Bus. The FX80 controller supports a full set of building automation features, such as scheduling, alarming, historical data collection and management, data sharing, energy management, totalization, customized control routines, tagging, templates, search, and hierarchies, which are specifically designed for commercial facilities.

Each FX80 controller includes a graphical system user interface with an HTML5 web profile, a configuration tool that you can access with the web browser, and robust security. Remote access is easily achieved using a wired or wireless connection from the Internet or intranet. Multiple users can connect to the FX80 controller concurrently. You can manage security and presentation preferences through user profiles, login IDs, and passwords.

The FX80 Supervisory Controller is a compact DIN rail mountable controller with the capability for remote external input and output points.

In addition, the FX80 controller's hardware and software design is modular, so you can plug in accessories, such as communications option modules, if needed. The device and point licensing

options allow you to select the device and point capacity most appropriate for the size of your facility and those options best needed to control it. And, in many cases, future expansions do not require the replacement of hardware.

Refer to the *FX80 Supervisory Controller Product Bulletin (LIT-12012250)* for important product application.

## FX80 features and benefits

### Fully commissioned and licensed out of the box

Allows you to power up, connect to a web browser, change default passwords, set up network parameters, and start adding your field controllers.

### Web-based user interface

Provides rich, graphical displays for system operation and analysis.

### Adoption of industry standard communication protocols

Allows for the integration of a wide variety of field controllers, including Facility Explorer field controllers and controllers provided by others without intermediate gateways or translators.

### Embedded Configuration Tool

Requires no proprietary or desktop software to configure the FX80 controller. You only need a web browser for basic configuration and monitoring.

### Modular design

Allows you to select only those components needed to meet specific project requirements.

### Small, compact design

Controller is easy to install.

## **FX Workbench**

Reduces engineering and installation time by providing you a way to easily and quickly create the FX80 database from field controller configurations offline.

## **Niagara® analytics**

Allows you to apply a variety of analytical algorithms and diagnostics to both historical and real-time data.

## **North American emissions compliance**

### **United States**

This equipment has been tested and found to comply with the limits for a Class A digital device pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when this equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area may cause harmful interference, in which case the users will be required to correct the interference at their own expense.

### **Warning (Part 15.21)**

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

### **Canada**

This Class (A) digital apparatus meets all the requirements of the Canadian Interference-Causing Equipment Regulations.

Cet appareil numérique de la Classe (A) respecte toutes les exigences du Règlement sur le matériel brouilleur du Canada.

### **Industry Canada Statement(s)**

This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions:

1. This device may not cause interference, and

2. This device must accept any interference, including interference that may cause undesired operation of the device.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes :

1. L'appareil ne doit pas produire de brouillage, et
2. L'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

## Ordering information

### FX80 Supervisory Controller ordering information

**Table 1: FX80 Supervisory Controller ordering information**

Region	Product code number	Description
North America	FX-SC8BDWIFI-0	FX80 Supervisory Controller and micro Secure Digital (SD) card, licensing required and purchased separately, disabled WLAN
EMEA	FX-SC8BDWIFI-0E	
North America	FX-SC8BASE-0	FX80 Supervisory Controller and micro Secure Digital (SD) card, licensing required and purchased separately
EMEA	FX-SC8BASE-0E	
North America / EMEA	FX-SC8BASE-700	Replacement FX80 Supervisory Controller, no micro SD card, no licenses

### FX80 bundle ordering information

**Table 2: EMEA**

Product code number	Description
FX-SC8D100M1-0E	FX80 Disabled Wifi, 100 points core license, Initial 18 months software maintenance for up to 499 points
FX-SC8D250M1-0E	FX80 Disabled Wifi, 250 points core license, Initial 18 months software maintenance for up to 499 points
FX-SC8D500M1-0E	FX-SC8D500M1-0E FX80 Disabled Wifi, 500 points core license, Initial 18 months software maintenance for up to 1249 points
FX-SC8D01KM1-0E	FX80 Disabled Wifi, 1250 points core license, Initial 18 months software maintenance for up to 4999 points
FX-SC8D05KM1-0E	FX80 Disabled Wifi, 5000 points core license, Initial 18 months software maintenance for up to 9999 points
FX-SC8D10KM1-0E	FX80 Disabled Wifi, 10000 points core license, Initial 18 months software maintenance for 10000 points
FX-SC8W100M1-0E	FX80 Wifi, 100 points core license, Initial 18 months software maintenance for up to 499 points
FX-SC8W250M1-0E	FX80 Wifi, 250 points core license, Initial 18 months software maintenance for up to 499 points
FX-SC8W500M1-0E	FX80 Wifi, 500 points core license, Initial 18 months software maintenance for up to 1249 points
FX-SC8W01KM1-0E	FX80 Wifi, 1250 points core license, Initial 18 months software maintenance for up to 4999 points
FX-SC8W05KM1-0E	FX80 Wifi, 5000 points core license, Initial 18 months software maintenance for up to 9999 points
FX-SC8W10KM1-0E	FX80 Wifi, 10000 points core license, Initial 18 months software maintenance for 10000 points

## FX80 core device licenses ordering information

**Table 3: North America**

Product code number	Description
FX-SC8CL005-0	FX80 Supervisory Controller core device license, 5 field devices, 250 points
FX-SC8CL010-0	FX80 Supervisory Controller core device license, 10 field devices, 500 points
FX-SC8CL025-0	FX80 Supervisory Controller core device license, 25 field devices, 1,250 points
FX-SC8CL100-0	FX80 Supervisory Controller core device license, 100 field devices, 5,000 points
FX-SC8CL200-0	FX80 Supervisory Controller core device license, 200 field devices, 10,000 points
FX-SC8CLDEMO-0	FX80 Supervisory Controller demo license, 500 field devices, 25,000 points. Enables all features needed to engineer and demonstrate FX Supervisory Controllers and FX Server stations. Intended for installing contractors. Requires annual support fee. Expires yearly.

**Table 4: EMEA**

Product code number	Description
FX-SC8CL100-0E	FX80 Supervisory Controller core device license, 100 points
FX-SC8CL250-0E	FX80 Supervisory Controller core device license, 250 points
FX-SC8CL500-0E	FX80 Supervisory Controller core device license, 500 points
FX-SC8CL01K-0E	FX80 Supervisory Controller core device license, 1,250 points
FX-SC8CL05K-0E	FX80 Supervisory Controller core device license, 5,000 points
FX-SC8CL10K-0E	FX80 Supervisory Controller core device license, 10,000 points
FX-SC8CLDEMO-0E	FX80 Supervisory Controller demo license, 25,000 points. Enables all features needed to engineer and demonstrate FX Supervisory Controllers and FX Server stations. Intended for installing contractors. Requires annual support fee. Expires yearly.

- Each FX80 controller requires the purchase of a single core device license.
- Device licenses are also dependent on point (proxy) counts. For each device that is licensed, 50 points are licensed. A 5-device core license also licenses 250 points. This could satisfy five devices with 25 points each or three devices with 80 points each. For three devices with 90 points each, you need to purchase the 10-device core license (or add a 5-device additional license to the 5-device core license).

## Initial purchase FX80 Controller software maintenance ordering information

**Table 5: North America**

Product code number	Description
FX-SC8D005M1-0	Initial 1 year software maintenance for FX80 Supervisory Controller with 5–9 field device capacity
FX-SC8D005M3-0	Initial 3 year software maintenance for FX80 Supervisory Controller with 5–9 field device capacity
FX-SC8D005M5-0	Initial 5 year software maintenance for FX80 Supervisory Controller with 5–9 field device capacity
FX-SC8D010M1-0	Initial 1 year software maintenance for FX80 Supervisory Controller with 10–24 field device capacity
FX-SC8D010M3-0	Initial 3 year software maintenance for FX80 Supervisory Controller with 10–24 field device capacity
FX-SC8D010M5-0	Initial 5 year software maintenance for FX80 Supervisory Controller with 10–24 field device capacity
FX-SC8D025M1-0	Initial 1 year software maintenance for FX80 Supervisory Controller with 25–99 field device capacity
FX-SC8D025M3-0	Initial 3 year software maintenance for FX80 Supervisory Controller with 25–99 field device capacity
FX-SC8D025M5-0	Initial 5 year software maintenance for FX80 Supervisory Controller with 25–99 field device capacity
FX-SC8D100M1-0	Initial 1 year software maintenance for FX80 Supervisory Controller with 100–199 field device capacity
FX-SC8D100M3-0	Initial 3 year software maintenance for FX80 Supervisory Controller with 100–199 field device capacity
FX-SC8D100M5-0	Initial 5 year software maintenance for FX80 Supervisory Controller with 100–199 field device capacity
FX-SC8D200M1-0	Initial 1 year software maintenance for FX80 Supervisory Controller with 200 and up field device capacity
FX-SC8D200M3-0	Initial 3 year software maintenance for FX80 Supervisory Controller with 200 and up field device capacity
FX-SC8D200M5-0	Initial 5 year software maintenance for FX80 Supervisory Controller with 200 and up field device capacity

**Table 6: EMEA**

Product code number	Description
FX-SC8P250M1-0E	Initial 1 year software maintenance for FX80 Supervisory Controller with 100 and 250 points
FX-SC8P250M3-0E	Initial 3 year software maintenance for FX80 Supervisory Controller with 100 and 250 points
FX-SC8P250M5-0E	Initial 5 year software maintenance for FX80 Supervisory Controller with 100 and 250 points
FX-SC8P500M1-0E	Initial 1 year software maintenance for FX80 Supervisory Controller with 500 points
FX-SC8P500M3-0E	Initial 3 year software maintenance for FX80 Supervisory Controller with 500 points

**Table 6: EMEA**

Product code number	Description
FX-SC8P500M5-0E	Initial 5 year software maintenance for FX80 Supervisory Controller with 500 points
FX-SC8P01KM1-0E	Initial 1 year software maintenance for FX80 Supervisory Controller with 1,250 points
FX-SC8P01KM3-0E	Initial 3 year software maintenance for FX80 Supervisory Controller with 1,250 points
FX-SC8P01KM5-0E	Initial 5 year software maintenance for FX80 Supervisory Controller with 1,250 points
FX-SC8P05KM1-0E	Initial 1 year software maintenance for FX80 Supervisory Controller with 5,000 points
FX-SC8P05KM3-0E	Initial 3 year software maintenance for FX80 Supervisory Controller with 5,000 points
FX-SC8P05KM5-0E	Initial 5 year software maintenance for FX80 Supervisory Controller with 5,000 points
FX-SC8P10KM1-0E	Initial 1 year software maintenance for FX80 Supervisory Controller with 10,000 points
FX-SC8P10KM3-0E	Initial 3 year software maintenance for FX80 Supervisory Controller with 10,000 points
FX-SC8P10KM5-0E	Initial 5 year software maintenance for FX80 Supervisory Controller with 10,000 points

- ① **Note:** Device capacity is equal to the sum of the core device license and any additional device license applied to the FX80 controller. Select the device capacity that is equal or lesser than the sum.

## FX80 Controller software maintenance (post initial) ordering information

**Table 7: North America**

Product code number	Description
FX-SC8D005M1-6	1 year software maintenance for FX80 Supervisory Controller with 5–9 field device capacity
FX-SC8D005M3-6	3 year software maintenance for FX80 Supervisory Controller with 5–9 field device capacity
FX-SC8D005M5-6	5 year software maintenance for FX80 Supervisory Controller with 5–9 field device capacity
FX-SC8D010M1-6	1 year software maintenance for FX80 Supervisory Controller with 10–24 field device capacity
FX-SC8D010M3-6	3 year software maintenance for FX80 Supervisory Controller with 10–24 field device capacity
FX-SC8D010M5-6	5 year software maintenance for FX80 Supervisory Controller with 10–24 field device capacity
FX-SC8D025M1-6	1 year software maintenance for FX80 Supervisory Controller with 25–99 field device capacity
FX-SC8D025M3-6	3 year software maintenance for FX80 Supervisory Controller with 25–99 field device capacity
FX-SC8D025M5-6	5 year software maintenance for FX80 Supervisory Controller with 25–99 field device capacity

**Table 7: North America**

Product code number	Description
FX-SC8D100M1-6	1 year software maintenance for FX80 Supervisory Controller with 100–199 field device capacity
FX-SC8D100M3-6	3 year software maintenance for FX80 Supervisory Controller with 100–199 field device capacity
FX-SC8D100M5-6	5 year software maintenance for FX80 Supervisory Controller with 100–199 field device capacity
FX-SC8D200M1-6	1 year software maintenance for FX80 Supervisory Controller with 200 and up field device capacity
FX-SC8D200M3-6	3 year software maintenance for FX80 Supervisory Controller with 200 and up field device capacity
FX-SC8D200M5-6	5 year software maintenance for FX80 Supervisory Controller with 200 and up field device capacity

**Table 8: EMEA**

Product code number	Description
FX-SC8P250M1-6E	1 year software maintenance for FX80 Supervisory Controller with 100 & 250 points
FX-SC8P250M3-6E	3 year software maintenance for FX80 Supervisory Controller with 100 & 250 points
FX-SC8P250M5-6E	5 year software maintenance for FX80 Supervisory Controller with 100 & 250 points
FX-SC8P500M1-6E	1 year software maintenance for FX80 Supervisory Controller with 500 points
FX-SC8P500M3-6E	3 year software maintenance for FX80 Supervisory Controller with 500 points
FX-SC8P500M5-6E	5 year software maintenance for FX80 Supervisory Controller with 500 points
FX-SC8P01KM1-6E	1 year software maintenance for FX80 Supervisory Controller with 1,250 points
FX-SC8P01KM3-6E	3 year software maintenance for FX80 Supervisory Controller with 1,250 points
FX-SC8P01KM5-6E	5 year software maintenance for FX80 Supervisory Controller with 1,250 points
FX-SC8P05KM1-6E	1 year software maintenance for FX80 Supervisory Controller with 5,000 points
FX-SC8P05KM3-6E	3 year software maintenance for FX80 Supervisory Controller with 5,000 points
FX-SC8P05KM5-6E	5 year software maintenance for FX80 Supervisory Controller with 5,000 points
FX-SC8P10KM1-6E	1 year software maintenance for FX80 Supervisory Controller with 10,000 points
FX-SC8P10KM3-6E	3 year software maintenance for FX80 Supervisory Controller with 10,000 points
FX-SC8P10KM5-6E	5 year software maintenance for FX80 Supervisory Controller with 10,000 points

**① Note:**

- Device capacity is equal to the sum of the core device license and any additional device license applied to the FX80 controller. Select the device capacity that is equal or lesser than the sum.

## FX80 Controller additional field device licenses ordering information

**Table 9: North America**

Product code number	Description
<b>Initial purchase</b>	
FX-SC8DL10-0	License enabling an additional 10 field devices, 500 points for one FX80, initial purchase only
FX-SC8DL25-0	License enabling an additional 25 field devices, 1,250 points for one FX80, initial purchase only
FX-SC8DL50-0	License enabling an additional 50 field devices, 2,500 points for one FX80, initial purchase only
<b>After initial purchase</b>	
FX-SC8DL10-6	License enabling an additional 10 field devices, 500 points for one FX80; upgrade after initial purchase
FX-SC8DL25-6	License enabling an additional 25 field devices, 1,250 points for one FX80; upgrade after initial purchase
FX-SC8DL50-6	License enabling an additional 50 field devices, 2,500 points for one FX80; upgrade after initial purchase

**Table 10: EMEA**

Product code number	Description
<b>Initial purchase</b>	
FX-SC8PL500-0E	License enabling an additional 500 points for one FX80, initial purchase only
FX-SC8PL01K-0E	License enabling an additional 1,250 points for one FX80, initial purchase only
FX-SC8PL02K-0E	License enabling an additional 2,500 points for one FX80, initial purchase only
<b>After initial purchase</b>	
FX-SC8PL500-6E	License enabling an additional 500 points for one FX80; upgrade after initial purchase
FX-SC8PL01K-6E	License enabling an additional 1,250 points for one FX80; upgrade after initial purchase
FX-SC8PL02K-6E	License enabling an additional 2,500 points for one FX80; upgrade after initial purchase

- ① **Note:** Additional devices are used to expand capacity from the core device license. For example, you can order the FX-SC8DL25-0 with the FX-SC8CL025-0 for a total of 50 devices, 2,500 points.



## Niagara analytics licenses ordering information

**Table 11: North America**

Product code number	Description
FX-ASCL100-0	License enabling 100 analytic points for Niagara Analytics on an FX80 Supervisory Controller at FX Supervisory Family Software Release 14.2 or greater
FX-ASCL250-0	License enabling 250 analytic points for Niagara Analytics on an FX80 Supervisory Controller at FX Supervisory Family Software Release 14.2 or greater
FX-ASCL500-0	License enabling 500 analytic points for Niagara Analytics on an FX80 Supervisory Controller at FX Supervisory Family Software Release 14.2 or greater
FX-ASCL1000-0	License enabling 1,000 analytic points for Niagara Analytics on an FX80 Supervisory Controller at FX Supervisory Family Software Release 14.2 or greater

**Table 12: EMEA**

Product code number	Description
FX-ASCL100-0E	License enabling 100 analytic points for Niagara Analytics on an FX80 Supervisory Controller at FX Supervisory Family Software Release 14.2 or greater. Only available to partners that are Niagara Analytics TCP trained.
FX-ASCL250-0E	License enabling 250 analytic points for Niagara Analytics on an FX80 Supervisory Controller at FX Supervisory Family Software Release 14.2 or greater. Only available to partners that are Niagara Analytics TCP trained.
FX-ASCL500-0E	License enabling 500 analytic points for Niagara Analytics on an FX80 Supervisory Controller at FX Supervisory Family Software Release 14.2 or greater. Only available to partners that are Niagara Analytics TCP trained.
FX-ASCL1000-0E	License enabling 1000 analytic points for Niagara Analytics on an FX80 Supervisory Controller at FX Supervisory Family Software Release 14.2 or greater. Only available to partners that are Niagara Analytics TCP trained.

- ① **Note:** Niagara Analytics products require Niagara Analytics N4 certification. Niagara Analytics certification training requires Niagara 4 TCP Certification.

## FX80 supporting software ordering information

**Table 13: FX80 supporting software ordering information**

Region	Product code number	Description
North America	FX-WBALM-0	License enabling Alarm Portal Client for FX Supervisory Family Software Release 14.2 or greater
EMEA	FX-WBALM-0E	

## FX80 Controller software accessories ordering information

**Table 14: North America**

Product code number	Description
FX-SC8LCCN-0	License enabling Carrier® Communication/Comfort Network (CCN) driver for one FX80 Supervisory Controller; initial purchase
FX-SC8LCCN-6	License enabling Carrier CCN driver for one FX80; upgrade after initial purchase
FX-SC8LAC-6	License enabling AC256 over RS-232 or RS-485 driver
FX-SC8LAINF-6	License enabling Andover® Infinity driver
FX-SC8LAPHP-6	License enabling American Auto-Matrix™ PHP over RS-232 or RS-485 driver
FX-SC8LAPUP-6	License enabling American Auto-Matrix™ PUP over RS-232 or RS-485 driver
FX-SC8LFLEX-6	License enabling Flex™ driver over RS-232 or RS-485
FX-SC8LMCQ-6	License enabling McQuay® driver to OPM driver
FX-SC8LVDRT-6	License enabling Veeder-Root® RS-232 or RS-485 driver

① **Note:** FX-SC8LAC-6 is available in Beta version only.

① **Note:** All 6.x license parts were discontinued on July 1, 2021 and are no longer available.

① **Note:** The FX-SC8LVDRT-6 is supported at FX Supervisory Family Software Release 6.3 only. This driver is not supported at FX Supervisory Family Software Release 14.x.

**Table 15: EMEA**

Product code number	Description
FX-SC8LCCN-0E	License enabling Carrier® Communication/Comfort Network (CCN) driver for one FX80 Supervisory Controller; initial purchase
FX-SC8LCCN-6E	License enabling Carrier CCN driver for one FX80; upgrade after initial purchase

## FX80 Controller hardware accessories ordering information

**Table 16: FX80 Controller hardware accessories ordering information**

Region	Product code number	Description
North America	FX-SC8SD-700	FX80 micro SD replacement (micro SD only); no licenses
EMEA	FX-SC8SD-700E	
North America	FX-SC8XLON-0	LonWorks FX80 expansion module for the FX80 Supervisory Controller
EMEA	FX-SC8XLON-0E	
North America	FX-SC8XD485-0	Dual port isolated RS-485 expansion module for the FX80 Supervisory Controller
EMEA	FX-SC8XD485-0E	
North America	FX-SC8X232-0	RS-232 expansion module for the FX80 Supervisory Controller
EMEA	FX-SC8X232-0E	
North America	FX-SC8AKIT-700	FX80 accessory kit including replacement connectors

**Table 16: FX80 Controller hardware accessories ordering information**

Region	Product code number	Description
EMEA	FX-SC8AKIT-700E	FX80 accessory kit including replacement connectors
North America	FX-SC8XKIT-700	FX80 expansion module kit including one-size-fits-all replacement connector
EMEA	FX-SC8XKIT-700E	FX80 expansion module kit including one-size-fits-all replacement connector
North America	FX-SC8XPS-0	FX80 universal wall mount power supply 100–240 VAC/24 V includes United States, Europe, United Kingdom, and Australia style plugs
EMEA	FX-SC8XPS-0E	FX80 universal wall mount power supply 100–240 VAC/24 V includes United States, Europe, United Kingdom, and Australia style plugs
EMEA	FX-SC8WKIT-700E	Extension cable and bracket for FX80 WLAN
North America	FX-SC8XIOR16-0	Remote input/output module for the FX Supervisory Controllers; includes 8 universal inputs, 4 relay outputs, and four 0-10 V analog outputs.
EMEA	FX-SC8XIOR16-0E	Remote input/output module for the FX Supervisory Controllers; includes 8 universal inputs, 4 relay outputs, and four 0-10 V analog outputs.
North America	FX-SC8XIOR34-0	Remote input/output module for the FX Supervisory Controllers; includes 16 universal inputs, 10 relay outputs, and eight 0-10 V analog outputs.
EMEA	FX-SC8XIOR34-0E	Remote input/output module for the FX Supervisory Controllers; includes 16 universal inputs, 10 relay outputs, and eight 0-10 V analog outputs.

## FX80 Controller - ESIGN and FIPS 140-2 accessories (North America only)

**Table 17: FX80 Controller - ESIGN and FIPS 140-2 accessories (North America only)**

Product code number	Description
FX-SC8FIPS-0	Provides FIPS 140-2 Level 1 conformance that uses the integrated FIPS-certified BouncyCastle module for an FX80. Compatible with FX version 14.6 and later.
FX-SC8LES250-0	License enabling e-signature application with 250 points for FX80
FX-SC8LESUNL-0	License enabling e-signature application with unlimited points for FX80
FX-SC8LESUP25-0	License adding 250 e-signature points for FX80
FX-TSES-0	E-signature technical support - up to 8 hours in 90-day period following order placement.

① **Note:** FX-TSES-0 is required with the first ESIGN order.

**Table 18: FX80 Controller - ESIGN EMEA**

Product code number	Description
FX-SC8LES250-0E	License enabling e-signature application with 250 points for FX80
FX-SC8LESUNL-0E	License enabling e-signature application with unlimited points for FX80
FX-SC8LESUP2-0E	License adding 250 e-signature points for FX80
FX-TSES-0E	E-signature technical support - up to 8 hours in 90-day period following order placement
FX-ESIGNELRN-0E	FX Niagara 4 e-signature Certification (E-learning)

① **Note:** FX-TSES-0E is required with the first ESIGN order.

**Table 19: FX80 Controller - JSON E-codes EMEA only**

Product code number	Description
FX-SC8LJSON-0E	License enabling JSON Toolkit for FX80 (Valid Software Maintenance required).

① **Note:** FX JSON Toolkit is only available in EMEA.

**FX80 is restricted from being sold in the following countries**

**Table 20: FX80 is restricted from being sold**

Country	Country Code	FX80 Part Number with Wi-Fi	FX80 Part Number with Wi-Fi Disabled
Cuba	—	Restricted from Sale	Restricted from Sale
Iran	—	Restricted from Sale	Restricted from Sale
North Korea	—	Restricted from Sale	Restricted from Sale
Sudan	—	Restricted from Sale	Restricted from Sale
Syria	—	Restricted from Sale	Restricted from Sale

## Technical specifications

**Table 21: FX80 Supervisory Controller**

<b>Enclosure/ mounting</b>	Plastic/DIN Rail
<b>Dimension</b>	179 mm x 110 mm x 61 mm (7.05 in. x 4.33 in. x 2.40 in.)
<b>Power supply</b>	24 VAC/DC
<b>Processor</b>	TI AM3352: 1000MHz ARM® Cortex™ A8
<b>RAM memory</b>	1 GB DDR3 SD RAM
<b>Flash memory</b>	Removable micro-SD card with 4 GB flash total storage, 2 GB user storage
<b>Environment</b>	Operating Temperature: -20°C to 60°C (-4°F to 140°F) Storage Temperature: -40°C to 85°C (-40°F to 185°F) Relative Humidity: 5% to 95%, noncondensing
<b>Onboard</b>	2 Ethernet 10/100 Mbps; 2 RS-485 (Isolated); 1 USB, 1 Micro USB, Fast USB Bus; Wi-Fi
<b>Plug-in options</b>	Dual port RS-485 (Isolated); LON FT/TP-10; RS-232
<b>Network drivers</b>	
<b>Embedded</b>	N2, BACnet, Niagara
<b>Direct I/O</b>	
<b>Onboard</b>	None
<b>Optional</b>	Up to 256 by using 16 Remote I/O Modules
<b>Local (NDIO)</b>	None
<b>Remote I/O</b>	Up to 256 I/O by using 16 Remote I/O Modules
<b>Compliance</b>	<p><b>United States</b> UL Listed, File E207782, CCN PAZX, under UL 916, Energy Management Equipment FCC compliant to CFR 47, part 15, subpart C, Class B</p> <p><b>Canada</b> UL Listed, File E207782, CCN PAZX7, under CSA C22.2 No. 205, Signal Equipment Industry Canada compliant to ICES-003</p> <p><b>Europe</b> CE Mark – Johnson Controls declares that this product is in compliance with the essential requirements and other relevant provisions of the EMC Directive.</p>

**Table 22: FX Workbench Requirements**

<b>Processor</b>	Intel® Pentium® 4, 1 GHz or higher 102 mm x 92 mm x 67 mm (4 x 3.625 x 2.625 in. )
<b>Operating System</b>	<b>32-bit:</b> Windows® 10 Pro or Enterprise, Windows 8 Pro or Enterprise, Windows 7 Professional, Enterprise, or Ultimate, or Windows XP® Professional <b>64-bit:</b> Windows® 10 Pro or Enterprise, Windows 8.1 Pro or Enterprise, Windows 8 Pro or Enterprise, Windows 7 Professional, Enterprise, or Ultimate, Windows Server 2012 Standard or Enterprise with SP2, or Windows Server® 2012 R2 Standard or Enterprise with SP2
<b>Memory</b>	1 GB minimum, 4 GB or more recommended for larger systems
<b>Hard disk</b>	4 GB minimum, more recommended depending on archiving requirements
<b>Network support</b>	Ethernet 10/100 Mbps with RJ-45 connector

- ① **Note:** The information relating to Processor in this table applies to both the FX Supervisory Software Release 14.x and FX Supervisory Software Release 6.x if using the AX license

### Product warranty

This product is covered by a limited warranty, details of which can be found at [www.johnsoncontrols.com/buildingswarranty](http://www.johnsoncontrols.com/buildingswarranty).

## Single point of contact

APAC	Europe	NA/SA
JOHNSON CONTROLS C/O CONTROLS PRODUCT MANAGEMENT NO. 32 CHANGJIANG RD NEW DISTRICT WUXI JIANGSU PROVINCE 214028 CHINA	JOHNSON CONTROLS VOLTAWEG 20 6101 XK ECHT THE NETHERLANDS	JOHNSON CONTROLS 507 E MICHIGAN ST MILWAUKEE WI 53202 USA

## Contact information

Contact your local branch office:  
[www.johnsoncontrols.com/locations](http://www.johnsoncontrols.com/locations)

Contact Johnson Controls:  
[www.johnsoncontrols.com/contact-us](http://www.johnsoncontrols.com/contact-us)